



SENNHEISER

790 - 865 MHz

Frequenzbereich Dw / Frequency range Dw

**Zusatzinformationen für Systeme der Serie
evolution wireless 300-500 G4**

**Additional information for Sennheiser
evolution wireless 300-500 G4 systems**

DE

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
790 - 865 MHz	75 MHz	max. 3000

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbänk sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In den Kanalbänken **U1 bis U6** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken **1 bis 20** sind in den Tabellen auf den folgenden zwei Seiten dargestellt.

Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

www.sennheiser.com/frequency-information

EN

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
790 - 865 MHz	75 MHz	max. 3000

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency banks **U1 to U6** allow the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The tables printed on the next two pages list the frequency presets in the frequency banks **1 to 20**.

Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

www.sennheiser.com/frequency-information

Sennheiser electronic GmbH & Co. KG

Am Labor 1, 30900 Wedemark, Germany, www.sennheiser.com
Publ. 04/18, 578634/A02

Frequenzbereich Dw / Frequency range Dw: 790 - 865 MHz

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	823.200	863.100	826.100	790.200	798.200	806.200	814.200	830.200	846.200	819.100
2	823.600	863.500	826.500	790.600	798.600	806.600	814.600	830.600	846.600	819.600
3	825.000	864.100	827.200	791.200	799.200	807.200	815.200	831.200	847.200	820.250
4	827.000	864.900	828.100	792.000	800.000	808.000	816.000	832.000	848.000	820.700
5	828.200	823.100	829.400	793.200	801.200	809.200	817.200	833.200	849.200	821.550
6	831.150	824.300	830.400	795.600	803.600	811.600	819.600	834.800	850.800	821.950
7	863.700	825.900	831.200	797.800	805.800	813.800	821.800	838.600	854.600	822.550
8	864.550	827.900	831.800	796.900	804.900	812.900	820.900	839.900	855.900	
9	824.200	830.100	863.100	792.475	800.475	808.475	816.475	842.600	858.600	
10	825.450	823.600	863.600	794.125	802.125	810.125	818.125	843.100	859.100	
11	826.100	829.200	864.800	794.575	802.575	810.575	818.575	844.800	860.800	
12	830.600	831.800	824.600	796.475	804.475	812.475	820.475	845.500	861.500	
13	831.900			801.950	809.950	817.950	825.950	846.750	863.250	
14	863.200			803.900	811.900	819.900	827.900	848.250	864.150	
15				806.600	814.600	822.600	830.600	848.900	790.200	
16				807.700	815.700	823.700	831.700	851.550	790.650	
17				810.350	818.350	826.350	834.350	857.000	791.300	
18				817.900	825.900	833.900	841.900	858.050	792.150	
19				819.500	827.500	835.500	843.500	862.750	795.000	
20				823.550	831.550	839.550	849.650	864.300	796.450	
21				826.400	834.400	843.750	850.800	790.200	798.300	
22				830.650	838.650	844.400	852.500	790.750	801.400	
23				834.500	842.500	850.600	856.750	791.850	801.950	
24				838.600	846.700	852.300	860.200	793.300	803.500	
25				844.150	855.550	857.000	864.750	795.400	805.800	
26				852.800	860.750	859.050	801.550	797.850	812.300	
27				855.250	863.250	864.650	790.375	802.900	814.650	
28				863.150	793.025	791.225	791.450	810.100	821.900	
29				863.700	835.175	794.950	791.950	816.050	828.550	
30				836.225	836.425	820.675	793.000	792.375	836.150	
31				839.175	839.625	837.725	797.025	796.725	792.675	
32				841.475	852.150	851.550	858.275	807.225	799.125	